

SUPERJOY HTTP-CGI Commands r3

MID 2021-10-22

Control Function	Command	Variable	Values	Comments
HDMI Output	http://[joystick ip]/cgi-bin/joystick.cgi?f=hdmiout&action=[action]	[joystick ip]	*joysticks current IP	
	Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=hdmiout&action=on	[action]	on off toggle	Enables HDMI output Disables HDMI output Toggles current HDMI output state
Custom Buttons	http://[joystick ip]/cgi-bin/joystick.cgi?f=custom&action=[action]&buttonid=[button id]	[joystick ip]	*joysticks current IP	
	Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=custom&action=trigger&buttonid=1	[action]	trigger	
		[button id]	1 2 3 4	Triggers Custom Button 1 Functions Triggers Custom Button 2 Functions Triggers Custom Button 3 Functions Triggers Custom Button 4 Functions
Camera Selection & HDMI Output Switching	http://[joystick ip]/cgi-bin/joystick.cgi?f=camselect&group=[group]&camid=[camera id]	[joystick ip]	*joysticks current IP	
	Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=camselect&group=2&camid=2	[group]	1 2 3 4 5	Selects Group 1 Selects Group 2 Selects Group 3 Selects Group 4 Selects Group 5 <i>Note, unique Camera ID Range</i>
		[camera id]	1 2 3 4 5 6 7 ... 170	Selects Camera 1 for Control & HDMI Output Selects Camera 2 for Control & HDMI Output Selects Camera 3 for Control & HDMI Output Selects Camera 4 for Control & HDMI Output Selects Camera 5 for Control & HDMI Output Selects Camera 6 for Control & HDMI Output Selects Camera 7 for Control & HDMI Output Group 5 Only - Allows for use of Camera IDs 1 - 170 End of Group 5 Camera ID Range
Direct Preset Recall	http://[joystick ip]/cgi-bin/joystick.cgi?f=directpresets&action=[action]&group=[group]&camid=[camera id]&preset=[preset]&presetspeed=[preset speed]	[joystick ip]	*joysticks current IP	
	Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=directpresets&action=recall&group=1&camid=1&preset=1&presetspeed=24	[action]	recall	
		[group]	1 2 3 4 5	Selects Group 1 Selects Group 2 Selects Group 3 Selects Group 4 Selects Group 5 <i>Note, unique Camera ID Range</i>
		[camera id]	1 2 3 4 5 6 7 ... 170	Selects Camera 1 for Control & HDMI Output Selects Camera 2 for Control & HDMI Output Selects Camera 3 for Control & HDMI Output Selects Camera 4 for Control & HDMI Output Selects Camera 5 for Control & HDMI Output Selects Camera 6 for Control & HDMI Output Selects Camera 7 for Control & HDMI Output Group 5 Only - Allows for use of Camera IDs 1 - 170 End of Group 5 Camera ID Range
		[preset]	0 ... 255	Selects Preset 0 for Recall (Start of Preset Range) ... Selects Preset 255 for Recall (Start of Preset Range)
		[preset speed]	1 ... 24 0	Selects a Preset Recall Speed of 1 ... Selects a Preset Recall Speed of 24 Selects the currently defined Preset Recall Speed
	Current Preset Recall	http://[joystick ip]/cgi-bin/joystick.cgi?f=presets&action=[action]&preset=[preset]&presetspeed=[preset speed]	[joystick ip]	*joysticks current IP
Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=presets&action=recall&preset=1&presetspeed=1		[action]	recall	Recalls a preset on whatever camera ID is currently selected
		[preset]	0 ... 255	Beginning of Preset Range ... End of Preset Range
		[preset speed]	1 ... 24 0	Selects a Preset Recall Speed of 1 ... Selects a Preset Recall Speed of 24 Selects the currently defined Preset Recall Speed
Inquiry				
Inquiry Function	Command	Variable	Values	Comments
Joystick Status Inquiry	http://[joystick ip]/cgi-bin/joystick.cgi?f=inquiry&action=[action]	[joystick ip]	*joysticks current IP	
	Example: http://192.168.100.88/cgi-bin/joystick.cgi?f=inquiry&action=status	[action]	status	
		[group]	1 2 3 4 5	Reporting Group 1 is currently selected Reporting Group 2 is currently selected Reporting Group 3 is currently selected Reporting Group 4 is currently selected Reporting Group 5 is currently selected
		[camera id]	1 2 3 4 5 6 7 ... 170	Reporting Camera 1 is currently selected for Control and HDMI output Reporting Camera 2 is currently selected for Control and HDMI output Reporting Camera 3 is currently selected for Control and HDMI output Reporting Camera 4 is currently selected for Control and HDMI output Reporting Camera 5 is currently selected for Control and HDMI output Reporting Camera 6 is currently selected for Control and HDMI output Reporting Camera 7 is currently selected for Control and HDMI output ... Unique to Group 5 ability to report Cameras 1 - 170 as selected for Control and HDMI output
		[preset]	0 ... 255	Reporting Preset 0 as last Preset Recalled (Start of Preset Range) ... Reporting Preset 255 as last Preset Recalled (End of Preset Range)
		[hdmii]	on off	Reporting the HDMI output is currently ENABLED Reporting the HDMI output is currently DISABLED

response example(json format):
{
 group:xx,
 camid:xx,
 preset:xx,
 hdmi:xx
}