

## HCM-1C

### Camera Ceiling Mount - Small Base Set Up Guide



## What's Included

- 1) Qty 1 - Ceiling Mount
- 2) Qty 1 - 1/4-20 mounting screw
- 3) Qty 1 - Lock Nut
- 4) Qty 2 - 1/4" washers



## STEP 1.

Screw 1” NPT pipe or pipe nipple tightly to a properly installed mounting plate or pipe flange like that shown below, engaging at least three full threads to ensure that it won’t fall. If using a 1.5” plate or flange, you must use a 1.5-1 inch reducer bushing.



### \*Notes:

Plate/flange, reducer bushing, & 1” NPT pipe or nipple not included.

Plate/flange must be installed according to applicable construction codes.

## STEP 2.

Screw lock nut onto pipe with teeth of nut facing down.



## STEP 3

Screw mount onto pipe securely, engaging at least 3 full threads.  
When aligned to desired location, tighten lock nut down to engage teeth into top of mount.



## STEP 4

Mount camera upright to top of mount or inverted to bottom of mount using included  $\frac{1}{4}$ -20 bolt through slot in mount. Use 0-2 of the provided washers as required to make bolt snug, so that camera is held in desired position.



## STEP 5

Run cabling through pipe or dress to outside of pipe for a clean installation aesthetic.